



more information



## INVERTER PRO 3000 E C5

PORTABLE POWER  
GENERATING SET Range PRESTIGE

### PRODUCT ADVANTAGES

Ergonomic, light and compact equipment  
Very Silent  
12 V output  
Quality current  
Low consumption

**INVERTER TECHNOLOGY** This new, very high performance technology guarantees the stability of the voltage and frequency of your genset to within  $\pm 1\%$  of the nominal value. Such high precision makes it possible to produce high-quality current and supply the most demanding equipment.

**12V OUTPUT** Supplies equipment operating off 12V and in particular for recharging batteries. Connection cables are included.

### Range PRESTIGE

Top of the range equipment that is efficient and with low noise emissions, for a wide range of standard requirements.



## INVERTER PRO 3000 E C5

### GENERAL SPECIFICATIONS

Range	PRESTIGE
Frequency (Hz)	50 Hz
Max power (kW)	3
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	13
75% cons. (l/h)	1,3
75% Autonomy (h)	10
Sound power level guaranteed LwA dB(A)	88
Acoustic pressure level @1m in dB(A)	73
Acoustic pressure level @7m in dB(A)	59

### ENGINE SPECIFICATIONS

Engine brand	YAMAHA
Engine ref.	MZ175_C5
Engine Type	O.H.V.
Start	Electrical Starter
Oil shutdown	Oui
Displacement (cm <sup>3</sup> )	171
Oil system capacity including filters (l)	0,6

### ALTERNATOR SPECIFICATION

Technology	Inverter
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

2 sockets 230V 16A - circuit breaker + 1 socket 12V 12A - circuit breaker + indicator

### DIMENSIONS AND WEIGHT

Length (cm)	68
Width (cm)	44,5
Height (cm)	55,5
Dry Weight (kg)	68

### PACKAGING

Packaging type	Box
Length (cm)	74,1
Width (cm)	55,1
Height (cm)	63,7
Weight (kg)	78
Pallet type	
Number of box by pallet	2
Pallet height (cm)	67
weight of the packaged Pallet (kg)	167

**KOHLER**

09 avr.. 25

INVERTER PRO 3000 E C5 - PORTABLE POWER – GENERATING SET PRESTIGE

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 – France – [portable.kohlerpower.com](http://portable.kohlerpower.com)



## INVERTER PRO 3000 E C5

### ACCESSORIES SUPPLIED

Spark plug spanner  
User and maintenance manual

### OPTIONS

**R05M** R05M - Manual source inverter for connecting a single-phase generator to a house

**3499231001875** RYS3 - Maintenance kit for INVERTER PRO 3000 including oil, spark plug and air filter

**3499231002827** RAP - Adapter from 16A industrial socket to 10/16A domestic socket

**RPQ** RPQ - 1m earth spike, supplied with 2m 10mm<sup>2</sup> mains cable