

# INVERTER PRO 3000 E C5

EAN 3499231003091



## PRODUCT ADVANTAGES

Ergonomic, light and compact equipment

Very Silent

12 V output

Quality current

Low consumption

**INVERTER TECHNOLOGY** This new, very high performance technology guarantees the stability of the voltage and frequency of your genset to within  $\pm 1\%$  of the nominal value. Such high precision makes it possible to produce high-quality current and supply the most demanding equipment.

**12V OUTPUT** Supplies equipment operating off 12V and in particular for recharging batteries. Connection cables are included.

## Range

### PRESTIGE

Top of the range equipment that is efficient and with low noise emissions, for a wide range of standard requirements.

**Fuel** Petrol

**Nominal voltage (V) | Number of Phase** 230 | Single phase

**Max power (kW)** 3 kW

**75% Autonomy (h)** 10

**Sound power level guaranteed LwA dB(A)** 88

**Dimensions L x W x H (cm) | Weight (kg)** 68 x 55,1 x 55,5 | 68

INVERTER PRO 3000 E C5 - GENERATING SET - PRESTIGE - 6 février 2026

[portable.rehlko.com](http://portable.rehlko.com)

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 – France

*This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.*



**SDMO Industries**  
accredited testing laboratory ISO 17025  
n°1-2171  
scope available on [www.cofrac.fr](http://www.cofrac.fr)





## GENERAL SPECIFICATIONS

<b>Range</b>	PRESTIGE
<b>Frequency (Hz)</b>	50 Hz
<b>Max power (kW)</b>	3
<b>Nominal voltage (V)</b>	230
<b>Number of Phase</b>	Single phase
<b>Assigned current (A)</b>	12,2
<b>Fuel</b>	Petrol
<b>Tank (L)</b>	13
<b>75% cons. (l/h)</b>	1,3
<b>75% Autonomy (h)</b>	10
<b>Sound power level guaranteed LwA dB(A)</b>	88
<b>Acoustic pressure level @1m in dB(A)</b>	73
<b>Acoustic pressure level @7m in dB(A)</b>	59



## ENGINE SPECIFICATIONS

<b>Engine brand</b>	YAMAHA
<b>Engine ref.</b>	MZ175_C5
<b>Start</b>	Electrical Starter
<b>Oil shutdown</b>	Oui
<b>Displacement (cm3)</b>	171
<b>Oil system capacity including filters (l)</b>	0,6



## ALTERNATOR SPECIFICATION

<b>Technology</b>	Inverter
<b>AVR Regulation</b>	No
<b>Indication of protection</b>	IP 23
<b>Insulation class</b>	H



## PLUGS AND PANEL DESCRIPTIVE

2 sockets 230V 16A - circuit breaker + 1 socket 12V 12A - circuit breaker + indicator



## DIMENSIONS AND WEIGHT

<b>Length (cm)</b>	68
<b>Width (cm)</b>	55,1
<b>Height (cm)</b>	55,5
<b>Dry Weight (kg)</b>	68



## PACKAGING

<b>Packaging type</b>	Box
<b>Length (cm)</b>	74,1
<b>Width (cm)</b>	55,1
<b>Height (cm)</b>	63,7
<b>Weight (kg)</b>	78
<b>Pallet type</b>	
<b>Number of box by pallet</b>	2
<b>Pallet height (cm)</b>	67
<b>weight of the packaged Pallet (kg)</b>	167

## ACCESSORIES SUPPLIED



Spark plug spanner  
User and maintenance manual

## Additional equipment



**R05M**

R05M - Manual transfert switch for connecting a single-phase generator to a house

---



**3499231001875**

RYS3 - Maintenance kit for INVERTER PRO 3000 including oil, spark plug and air filter

---



**3499231002827**

RAP - Adapter from 16A industrial socket to 10/16A domestic socket

---



**RPQ**

RPQ - 1m earth spike, supplied with 2m 10mm<sup>2</sup> mains cable

---