



more information

PERFORM 3000 XL C5



PERFORM 3000 XL C5

PORTABLE POWER

GENERATING SET Range PERFORM XL

PRODUCT ADVANTAGES

Compact frame with protection panels against shocks
 Starting up facilitated thanks to the summer/winter positions
 KOHLER air-cooled industrial engine
 Good value for money
 Generating set guaranteed 3 years

QUAD CLEAN AIR FILTER The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range PERFORM XL

An efficient, cost effective and easy to handle equipment, suitable for frequent use.



GENERAL SPECIFICATIONS

Range	PERFORM XL
Frequency (Hz)	50 Hz
Max power (kW)	2,8
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	13
75% cons. (l/h)	1,3
75% Autonomy (h)	10
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine ref.	CH270_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	208
Oil system capacity including filters (l)	0,6

ALTERNATOR SPECIFICATION

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	65
Width (cm)	51
Height (cm)	46
Dry Weight (kg)	46,5

PACKAGING

Packaging type	Box
Length (cm)	66
Width (cm)	52,5
Height (cm)	47
Weight (kg)	48,5
Pallet type	140/110
Number of box by pallet	12
Pallet height (cm)	154
weight of the packaged Pallet (kg)	598



PERFORM 3000 XL C5

ACCESSORIES SUPPLIED

Funnel
User and maintenance manual
Floor maintaining slot
Ergonomic handle grip

OPTIONS

R05M	R05M - Manual source inverter for connecting a single-phase generator to a house
3499231002575	RKB1HD - Trolley kit for PERFORM / PERFORM XL / TECHNIC 6500 - 7500T / DIESEL / WELDARC 200 - 220 ; Puncture-proof wheels Ø 290 mm
3499231005040	RKS6 - Maintenance kit for PERFORM 3000 XL including oil, spark plug, fuel filter and air filter
RHO	RHO - Protective cover for HX 3000 / HXC 3000 / PERFORM 3000 - 3000 XL / PRESTIGE 3000 / ST 2,36 - 3,60 / TR 2,36 - 3,60 / HP 2,26 / XT 3,78 ; Dimensions : 70 x 45 x 50 cm
RPM	RPM - Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket
RPQ	RPQ - 1m earth spike, supplied with 2m 10mm ² mains cable
RKD1	RKD1 - Kit of 2 removable differential adaptors for domestic sockets 16A
3499231000762	RLIFT1 - Central lifting yoke for PERFORM 3000 - 3000 XL
3499231920831	GSC - Generator Smart Care : Bluethooth box which can be used on all portable generator