



more information

**HX 3000 C5**

PORTABLE POWER

GENERATING SET Range INTENS

PRODUCT ADVANTAGES

Solid and high-performance equipment
Generating set guaranteed 3 years
HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.

**HX 3000 C5****GENERAL SPECIFICATIONS**

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW)	2,7
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3,1
75% cons. (l/h)	1,3
75% Autonomy (h)	2,4
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX200_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	196
Oil system capacity including filters (l)	0,6

ALTERNATOR SPECIFICATION

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	41

PACKAGING

Packaging type	Box
Length (cm)	60,5
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	5
Pallet height (cm)	57
weight of the packaged Pallet (kg)	231



HX 3000 C5

ACCESSORIES SUPPLIED

Funnel
User and maintenance manual

OPTIONS

R05M	R05M - Manual source inverter for connecting a single-phase generator to a house
R06	R06 - Trolley kit for HX 3000 / HXC 3000 / PRESTIGE 3000 ; Puncture-proof wheels Ø 187 mm
3499231033104	R18 - Maintenance kit for HX 3000 including oil, spark plug and air filter
RBH1	RBH1 - Box of 20 cans of 1L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE
RBH0-5	RBHO-5 - Box of 24 cans of 0.5L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE
RHO	RHO - Protective cover for HX 3000 / HXC 3000 / PERFORM 3000 - 3000 XL / PRESTIGE 3000 / ST 2,36 - 3,60 / TR 2,36 - 3,60 / HP 2,26 / XT 3,78 ; Dimensions : 70 x 45 x 50 cm
RPM	RPM - Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket
RPQ	RPQ - 1m earth spike, supplied with 2m 10mm2 mains cable
RKD1	RKD1 - Kit of 2 removable differential adaptors for domestic sockets 16A
3499231920831	GSC - Generator Smart Care : Bluettooth box which can be used on all portable generator