



HX 4000 C5

PORTABLE POWER

GENERATING SET Range INTENS

PRODUCT ADVANTAGES

Solid and high-performance equipment
Generating set guaranteed 3 years
HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



HX 4000 C5

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW)	3,7
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	5,3
75% cons. (l/h)	2,1
75% Autonomy (h)	2,5
Sound power level guaranteed LwA dB(A)	96
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX270_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	270
Oil system capacity including filters (l)	1,1

ALTERNATOR SPECIFICATION

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	71,5
Width (cm)	57
Height (cm)	49
Dry Weight (kg)	56

PACKAGING

Packaging type	Box
Length (cm)	73
Width (cm)	58
Height (cm)	49,5
Weight (kg)	58,5
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	162
weight of the packaged Pallet (kg)	361

ACCESSORIES SUPPLIED

Funnel
User and maintenance manual

OPTIONS

R01	This set includes the hour meter and the differential circuit breaker
R05M	The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut
RKB2	Trolley kit for the generating sets superior to 6kW
3499231001585	R33 - Maintenance kit for Honda GX270
RH1	Cover for SDMO 's generating sets, welding sets and water pumps
RPM	Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
RPQ	For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm ² cable
RKD1	kit of two diferential removable adapters for domestic sockets. Schema for ground bonding with isolated neutral
3499231004555	GSC - GENERATOR SMART CARE, the Bluetooth module for monitoring the maintenance of generators, maintenance and diagnostics