



## HX 6000 C5

PORTABLE POWER

GENERATING SET Range INTENS

### PRODUCT ADVANTAGES

Solid and high-performance equipment  
Generating set guaranteed 3 years  
HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

### Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



## HX 6000 C5

### GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW)	5,6
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	6,1
75% cons. (l/h)	2,5
75% Autonomy (h)	2,4
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

### ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX390_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	389
Oil system capacity including filters (l)	1,1

### ALTERNATOR SPECIFICATION

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 32A socket- circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	77
Width (cm)	57
Height (cm)	59
Dry Weight (kg)	79

### PACKAGING

Packaging type	Box
Length (cm)	78,5
Width (cm)	58
Height (cm)	59,5
Weight (kg)	81,5
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	192
weight of the packaged Pallet (kg)	499

### ACCESSORIES SUPPLIED

Funnel  
User and maintenance manual

### OPTIONS

- R02** This set includes the hour meter and the differential circuit breaker
- R05M** The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut
- RKB2** Trolley kit for the generating sets superior to 6kW
- 3499231033203** R19 - Maintenance kit for Honda GX390 engines (except Alizé 6000E and Alizé 7500 TE)
- RH1** Cover for SDMO 's generating sets, welding sets and water pumps
- RPM** Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
- RPQ** For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm<sup>2</sup> cable
- 3499231004555** GSC - GENERATOR SMART CARE, the Bluetooth module for monitoring the maintenance of generators, maintenance and diagnostics