



more information

**HX 6000 C5**

PORTABLE POWER

GENERATING SET Range INTENS

PRODUCT ADVANTAGES

Solid and high-performance equipment
Generating set guaranteed 3 years
HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.

**HX 6000 C5****GENERAL SPECIFICATIONS**

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW)	5,6
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	6,1
75% cons. (l/h)	2,5
75% Autonomy (h)	2,4
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX390_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	389
Oil system capacity including filters (l)	1,1

ALTERNATOR SPECIFICATION

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 32A socket- circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	77
Width (cm)	57
Height (cm)	59
Dry Weight (kg)	79

PACKAGING

Packaging type	Box
Length (cm)	78,5
Width (cm)	58
Height (cm)	59,5
Weight (kg)	81,5
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	192
weight of the packaged Pallet (kg)	499



HX 6000 C5

ACCESSORIES SUPPLIED

Funnel
User and maintenance manual

OPTIONS

R05M R05M - Manual source inverter for connecting a single-phase generator to a house

RKB2 RKB2 - Trolley kit for HX 4000 - 6000 - 7500T / HXC 4000 - 6000 - 7500T / TECHNIC 10000 - 15000 / VX 200/4 - 220-7,5 / WELDARC 300 / TRASH ; Puncture-proof wheels Ø 290 mm

3499231033203 R19 - Maintenance kit for HX 6000 - 7500 T / VX 200/4 including oil, spark plug and air filter

RH1 RH1 - Protective cover for HX 4000 - 6000 - 7500T / HXC 4000 - 6000 - 7500T / PERFORM 4500 - 4500 XL - 5500T - 5500 T XL - 6500 - 6500 XL - 7500 T - 7500 XL / TECHNIC 6500 - 7500 TE / DIESEL / TRASH ; Dimensions : 82 x 58 x 50 cm

RPM RPM - Plug kit for all models: 2 x 16A / 230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket

RPQ RPQ - 1m earth spike, supplied with 2m 10mm² mains cable

3499231920831 GSC - Generator Smart Care : Bluettooth box which can be used on all portable generator