

KOHLER®



HX 7500 T C5

PORTABLE POWER

GENERATING SET Range INTENS

PRODUCT ADVANTAGES

Solid and high-performance equipment
Generating set guaranteed 3 years
HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



HX 7500 T C5

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW)	5,7
Max power (kVA)	7,1
Nominal voltage (V)	400
Number of Phase	Three phase
Fuel	Petrol
Tank (L)	6,1
75% cons. (l/h)	2,5
75% Autonomy (h)	2,4
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX390_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	389
Oil system capacity including filters (l)	1,1

ALTERNATOR SPECIFICATION

Technology	Collar and brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 400V 16A socket - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	77
Width (cm)	57
Height (cm)	59
Dry Weight (kg)	80

PACKAGING

Packaging type	Box
Length (cm)	78,5
Width (cm)	58
Height (cm)	59,5
Weight (kg)	82,5
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	192
weight of the packaged Pallet (kg)	505

KOHLER®

HX 7500 T C5 - PORTABLE POWER – GENERATING SET INTENS

15 oct.. 23

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 – France – portable.kohlerpower.com

ACCESSORIES SUPPLIED

Funnel
User and maintenance manual

OPTIONS

- R03** This set includes the hour meter and the differential circuit breaker
- VERSO10T40A** The manual changeover switch is used to connect and disconnect a 3-phases generating set manually to a domestic circuit when there is a power cut.
- RKB2** Trolley kit for the generating sets superior to 6kW
- 3499231033203** R19 - Maintenance kit for Honda GX390 engines (except Alizé 6000E and Alizé 7500 TE)
- RH1** Cover for SDMO 's generating sets, welding sets and water pumps
- RPM** Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
- RPQ** For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable
- 3499231004555** GSC - GENERATOR SMART CARE, the Bluetooth module for monitoring the maintenance of generators, maintenance and diagnostics