



more information



## TECHNIC 7500 TE C5

PORTABLE POWER

GENERATING SET Range TECHNIC

### PRODUCT ADVANTAGES

Generating set guaranteed 3 years  
 KOHLER air-cooled industrial engine  
 Connection interface equipped with an hour meter  
 Electric starter with batteries without maintenance  
 Large Autonomy

GENERATOR SMART CARE is a Bluetooth box which can be used on all the brand's portable generators.

TECHNOLOGY EQUIPPED WITH AN INNOVATIVE APPLICATION Generator Smart Care is a digital solution which provides access to:

- The list of generators
- The maintenance due dates
- A maintenance aid
- The map of reseller partners

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

### Range TECHNIC

A long run time equipment that can withstand extreme conditions, for daily professional use.



## TECHNIC 7500 TE C5

### GENERAL SPECIFICATIONS

|  |             |
|--|-------------|
| Range                                  | TECHNIC     |
| Frequency (Hz)                         | 50 Hz       |
| Max power (kW)                         | 6,5         |
| Max power (kVA)                        | 8,1         |
| Nominal voltage (V)                    | 400         |
| Number of Phase                        | Three phase |
| Fuel                                   | Petrol      |
| Tank (L)                               | 18          |
| 75% cons. (l/h)                        | 2,6         |
| 75% Autonomy (h)                       | 6,9         |
| Sound power level guaranteed LwA dB(A) | 99          |
| Acoustic pressure level @1m in dB(A)   | 83          |
| Acoustic pressure level @7m in dB(A)   | 69          |

### ENGINE SPECIFICATIONS

|   |                    |
|---|--------------------|
| Engine brand                              | KOHLER             |
| Engine ref.                               | CH440E_C5          |
| Engine Type                               | O.H.V.             |
| Start                                     | Electrical Starter |
| Oil shutdown                              | Oui                |
| Displacement (cm <sup>3</sup> )           | 429                |
| Oil system capacity including filters (l) | 1,3                |

### ALTERNATOR SPECIFICATION

|                          |                  |
|--------------------------|------------------|
| Technology               | Collar and brush |
| AVR Regulation           | No               |
| Indication of protection | IP 23            |
| Insulation class         | H                |

### PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 400V 16A socket - circuit breaker + hour meter

### DIMENSIONS AND WEIGHT

|                 |       |
|-----------------|-------|
| Length (cm)     | 81    |
| Width (cm)      | 55,5  |
| Height (cm)     | 59    |
| Dry Weight (kg) | 108,5 |

### PACKAGING

|                                    |        |
|------------------------------------|--------|
| Packaging type                     | Box    |
| Length (cm)                        | 82     |
| Width (cm)                         | 56,5   |
| Height (cm)                        | 60     |
| Weight (kg)                        | 110,5  |
| Pallet type                        | 120/80 |
| Number of box by pallet            | 6      |
| Pallet height (cm)                 | 193    |
| weight of the packaged Pallet (kg) | 673    |



**KOHLER**

09 avr.. 25

TECHNIC 7500 TE C5 - PORTABLE POWER – GENERATING SET TECHNIC

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 – France – [portable.kohlerpower.com](http://portable.kohlerpower.com)



## TECHNIC 7500 TE C5

### ACCESSORIES SUPPLIED

Funnel  
User and maintenance manual  
Floor maintaining slot  
Ergonomic handle grip  
Battery without maintenance

### OPTIONS

|                      |   |
|----------------------|---|
| <b>3499231004012</b> | VERSO 10 T 40A - Manual source inverter for connecting a three-phase generator to a house   |
| <b>3499231002575</b> | RKB1HD - Trolley kit for PERFORM / PERFORM XL / TECHNIC 6500 - 7500T / DIESEL / WELDARC 200 - 220 ; Puncture-proof wheels Ø 290 mm  |
| <b>3499231005057</b> | RKS7 - Maintenance kit for PERFORM 4500 XL - 5500T XL - 6500 XL - 7500T XL / TECHNIC 6500 - 7500T including oil, spark plug, fuel filter and air filter   |
| <b>RH1</b>           | RH1 - Protective cover for HX 4000 – 6000 – 7500T / HXC 4000 – 6000 – 7500T / PERFORM 4500 – 4500 XL – 5500T – 5500 T XL – 6500 – 6500 XL – 7500 T – 7500 XL / TECHNIC 6500 – 7500 TE / DIESEL / TRASH ; Dimensions : 82 x 58 x 50 cm |
| <b>RPM</b>           | RPM - Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket   |
| <b>RPQ</b>           | RPQ - 1m earth spike, supplied with 2m 10mm2 mains cable  |
| <b>3499231000786</b> | RLIFT2 - Central lifting yoke for PERFORM 4500 XL- 6500 – 6500 XL / TECHNIC 6500 – 7500T  |